



TO247-3L Plastic-Encapsulate IGBT

CCGB50T65HDT

IGBT in Trench FS Technology

$V_{(BR)CES}$	V_{CEsat}		I_C	
	650V	$T_{vj}=25^{\circ}C$	1.6V@50A	$T_{vj}=25^{\circ}C$
$T_{vj}=150^{\circ}C$		1.9V@50A	$T_{vj}=150^{\circ}C$	50A

Features:



- 650V Trench field-stop technology
- Low conduction and switching losses
- Positive temperature coefficient of forward voltage
- Short Circuit withstand time-10 μ s
- AEC Q101 qualified

Applications:

- Automobile PTC
- Short-Circuit Protector
- UPS Power
- Electric Welding Machine

Key Performance and Package Parameters

Type	V_{CE}	I_C	V_{CEsat} $T_{vj}=25^{\circ}C@50A$	T_{vjmax}	Marking	Package
CCGB50T65HDT	650V	50A	1.6V	175 $^{\circ}C$	CCGB50T65HDT	PG-TO247-3L



TO-247-3L

Maximum Rated Values

Parameter	Symbol	Value	Unit
Collector emittervoltage	V_{CE}	650	V
DC collector current, $T_C=25^{\circ}\text{C}$	I_C	100	A
DC collector current, $T_C=100^{\circ}\text{C}$	I_C	50	A
Pulsed collector current, t_p limited by T_{vjmax}	I_{Cplus}	200	A
Diode forward current, $T_C=25^{\circ}\text{C}$	I_F	100	A
Diode forward current, $T_C=100^{\circ}\text{C}$	I_F	50	A
Diode pulsed current, t_p limited by T_{vjmax}	I_{Fplus}	200	A
Gate emitter voltage	V_{GE}	± 20	V
Short circuit with stand time, $V_{GE}=15\text{V}$, $V_{CC}=400\text{V}$, $T_{vj}=175^{\circ}\text{C}$	t_{SC}	10	μs
Power dissipation , $T_C=25^{\circ}\text{C}$	P_{tot}	366	W
Operating junction temperature	T_{vj}	-40~+175	$^{\circ}\text{C}$
Storage temperature	T_{stg}	-55~+175	$^{\circ}\text{C}$

Thermal Resistance

Parameter Characteristic	Symbol	Value	Unit
IGBT thermal resistance, junction-case	R_{thjc}	0.41	K/W
FRD thermal resistance, junction-case	R_{thjc}	0.81	K/W
Thermal resistance junction to ambient	R_{thja}	50	K/W

Static Characteristics, $T_C=25^\circ\text{C}$, unless otherwise specified


Parameter	Symbol	Conditions	Value			Unit	
			min	typ	max		
Collector emitter break down voltage	$V_{(BR)CES}$	$V_{GE}=0V, I_C=1mA$	650	-	-	V	
Collector emitter saturation voltage	V_{CEsat}	$V_{GE}=15V, I_C=50A$	$T_{vj}=25^\circ\text{C}$	-	1.6	1.9	V
			$T_{vj}=150^\circ\text{C}$	-	1.9		
Diode forward voltage	V_F	$V_{GE}=0V, I_F=50A$	$T_{vj}=25^\circ\text{C}$	-	1.83	2.1	V
			$T_{vj}=150^\circ\text{C}$	-	1.68		
Gate emitter threshold voltage	V_{GEth}	$I_C=1mA, V_{CE}=V_{GE}$	4.8	5.7	6.2	V	
Zero gate voltage collector current	I_{CES}	$V_{CE}=650V, V_{GE}=0V$	-	-	4	μA	
Gate emitter leakage current	I_{GES}	$V_{CE}=0V, V_{GE}=20V$	-	-	200	nA	

Switching Characteristic, at $T_C=25^\circ\text{C}$, unless otherwise specified


Parameter	Symbol	Conditions	Value			Unit
			min	typ	max	
IGBT Characteristic						
Input capacitance	C_{ies}	$V_{CE}=25V, V_{GE}=0V, f=100kHz$	-	2220	-	pF
Output capacitance	C_{oes}		-	125	-	
Reverse transfer capacitance	C_{res}		-	27	-	
Gate resistance	R_g	$f=100kHz$	-	3.1	-	Ω
Turn-on delay time	t_{don}	$V_{CE}=400V, V_{GE}=-8V/+15V, R_g=10\Omega, I_C=40A, \text{Inductive Load}$	-	46	-	ns
Rise time	t_r		-	154	-	ns
Turn-off delay time	t_{doff}		-	120	-	ns
Fall time	t_f		-	134	-	ns
Turn-on energy	E_{on}		-	2.5	-	mJ
Turn-off energy	E_{off}		-	1.1	-	mJ
FRD Characteristic						
Reverse recovery time	t_{rr}	$V_R=400V, R_g=10\Omega, I_F=40A, \text{Inductive Load}$	-	33	-	ns
Recovery charge	Q_r		-	65	-	μC
Peak recovery current	I_{RM}		-	25	-	A

Typical Characteristic Curve


Typical output characteristic ($T_c=25^\circ\text{C}$)




Typical output characteristic ($T_c=125^\circ\text{C}$)




Typical transfer characteristic




Typical collector-emitter saturation voltage as a function of case temperature




Typical switching times as a function of gate resistor




Typical switching energy losses as a function of gate resistor




Typical switching times as a function of collector current




Typical switching energy losses as a function of collector current




Typical FRD forward current as a function of forward voltage




Typical reverse recovery time as a function of FRD forward current




Typical reverse recovery charge as a function of FRD forward current




Typical capacitance as a function of collector-emitter voltage




Typical gate charge



FBSOA



PG-TO247-3OutlineDimensions



DIM	MILLIMETERS		INCHES	
	MIN	MAX	MIN	MAX
A	4.83	5.21	0.190	0.205
A1	2.27	2.54	0.089	0.100
A2	1.85	2.16	0.073	0.085
b	1.07	1.33	0.042	0.052
b1	1.90	2.41	0.075	0.095
b2	1.90	2.16	0.075	0.085
b3	2.87	3.38	0.113	0.133
b4	2.87	3.13	0.113	0.123
c	0.55	0.68	0.022	0.027
D	20.80	21.10	0.819	0.831
D1	16.25	17.65	0.640	0.695
D2	0.95	1.35	0.037	0.053
E	15.70	16.13	0.618	0.635
E1	13.10	14.15	0.516	0.557
E2	3.68	5.10	0.145	0.201
E3	1.00	2.60	0.039	0.102
e	5.44 (BSC)		0.214 (BSC)	
N	3		3	
L	19.80	20.32	0.780	0.800
L1	4.10	4.47	0.161	0.176
ϕP	3.50	3.70	0.138	0.146
Q	5.49	6.00	0.216	0.236
S	6.04	6.30	0.238	0.248

NOTICE

Cloudchild reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Cloudchild does not assume any liability arising out of the application or use of any product described herein.

ChongQing Cloudchild Technology Co., Ltd. (short for Cloudchild) exerts the greatest possible effort to ensure high quality and reliability. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing Cloudchild products, to comply with the standards of safety in making a safe design for the entire system, including redundancy, fire-prevention measures, and malfunction prevention, to prevent any accidents, fires, or community damage that may ensue. In developing your designs, please ensure that Cloudchild products are used within specified operating ranges as set forth in the most recent Cloudchild products specifications.

Dateofchange	Rev#	revisecontent
2023/06/29	A/0	/